

# M-1A SERIES

## MICRO INFRARED REPEATER

The M-1A Series enables the homeowner to operate virtually any infrared-controlled stereo/video component from multiple room locations. Ultra-sensitive receiver provides fast reaction time and minimal interference within a 40-foot range. Simply aim a remote toward any M-1A Series repeater. Once the command is received, the M-1A Series will re-broadcast the infrared command to a small "flasher" LED located on the front of each component. The system is powered by a 9VDC-12VDC (200-500mA) power supply (such as Atlas Sound Model PS-M12) or plug-in adapter.

The M-1A Series was designed to be unobtrusive. It features an attractive, flush, white lens that blends with any surface.

Unit is available installed on a white wall plate (Model M-1AJW) it can be flush-mounted (Model M-1A) to a cabinet, wall, ceiling, or speaker grille. Connection to the M-1A is easily achieved through a clearly marked three point terminal block attached directly to the unit.

### Models:

#### M-1A

Flush-mount cabinet/ceiling/wall repeater. Requires a 1/2" drilled hole in order to be mounted.

#### M-1AJW

Decora-style white subplate mounts in a standard outlet box and requires a standard cover plate.

## Single Repeater/Emitter System

### MODEL F-1 FLASHER/EMITTER

**Note:** Atlas Sound F-1 Infrared Flashers can be parallel wired. Up to six can be connected to control six sources.

