



AAVC-10K

10K Ω Remote Level Control



AAVC-10K

Features

- 10k Ω Linear Taper Insures Smooth Level Control
- Attractive Decora Style Wall Plate in Ivory and White Finishes
- Convenient Kit Includes Hardware
- Simple 2 Conductor Wiring

General Description

The AAVC-10K Remote Level Control is perfect for use in applications requiring remote volume level control of music or microphone. Designed to be used with Atlas Sound AA120, AA240, AA120M amplifiers, and the AA-ML Mic/Line Input Module, this kit includes Decora Style wall plate, insert, and knob in both industry standard white and ivory finishes.

Kit Contains:

- (1) Pot and Hardware
- (1) Metal Back Plate
- (2) Knobs, 1 White & 1 Ivory
- (2) Decora Trim Plates, 1 White & 1 Ivory
- (2) Trim Inserts, 1 White & 1 Ivory
- (4) Plate Screws $\frac{9}{32}$ X .5 PH, 2 White & 2 Ivory

Specifications

Height	4 $\frac{3}{4}$ " (121mm)
Width	2 $\frac{15}{16}$ " (75mm)
Depth	2 $\frac{2}{5}$ " (60.9mm)
Mounting	Fits into Standard E.O. Backbox

Instructions: Connecting a Remote Level Control

1. Decide on the color of Decora wall plate that fits the room.
2. Run a two conductor wire from the remote level control location to the amplifier rack. We suggest using 20 gauge wire for distances less than 1000 ft. It is recommended to use wire with an additional outer protective sleeve over the two conductors. **Note:** Consult with your local authorities on wiring codes within the area.
3. Connect the 2 wires to the pot and to the Phoenix connector on the amp labeled VCA. **Note:** There is no polarity to the wiring.
4. Refer to the owner's manual of the amplifier/module for proper settings.

