

1. Once the Atlas Sound DSP Series software is installed, click the shortcut labeled DSP Soundmasking Control shown in Figure 1.





2. The software should open and auto find the unit, shown in Figure 2. If the software does not auto find the unit, then the USB driver may require updating.

Atlas Sound					
🖉 Atlas So	ound	I	DSP Series Masking Control Software		
File Help	Manual toles		×		
System Diagram	Found 1 units Search again				
LINE 1         TONI           UIPE 2         TONI           UIPE 2         TONI           MAGE         TONI           MCC         COMPRESS           NETHONS         TONI           TECCO         COMPRESS           NODE1         VEL           NODE2         VEL           NODE2         VEL	Unit Type MAC/Pert MicroMaskitSerial COM5	Name	Run Time Details		
NOSE RAMP	Unit Name Database: (none loaded) Load Unit Name Database File Save Unit Names to Database File		Name/Rename this unit Connect to this unit		
		1	Exit		
			Ready		

Figure 2



## DSP2210 / DSP2212

Quick Procedure for Updating the USB Driver

- 3. If an error message occurs regarding updating the USB driver, follow these steps.
- 4. Click on "System" from the Control Panel screen.

ç djust your computer's settings				View by: Small kons 🔻
Action Center	Constrative Tools	💿 Akamai NetSession Interface Control P	🛶 Autodesk Plot Style Manager	G Jag Autodesk Plotter Manager
AutoPlay	Backup and Restore	Biometric Devices	RtLocker Drive Encryption	📓 Color Management
Credential Manager	Plate and Time	Default Programs	🛒 Desktop Gadgets	鐞 Device Manager
Devices and Printers	🖉 Display	C Ease of Access Center	Flash Player (32-bit)	Folder Options
Fonts	Getting Started	NomeGroup	HP Quick Launch Buttons	Indexing Options
Internet Options	🔬 Java (32-bit)	- Keyboard	Location and Other Sensors	() Mail (32-bit)
Mouse	Network and Sharing Center	I Notification Area Icons	NVIDIA Control Panel	WIDIA nView Desktop Manager
Parental Controls	Performance Information and Tools	Series Personalization	A Phone and Modern	Power Options
Programs and Features	Recovery	🍠 Region and Language	🕷 RemoteApp and Desktop Connections	Sound
Speech Recognition	Sync Center	<ul> <li>System</li> </ul>	L Taskbar and Start Menu	Troubleshooting
User Accounts	Windows CardSpace	Windows Defender	Windows Firewall	Windows Mobility Center
Windows Update				

Figure 3

- 5. Locate the device manager on the computer in the Control Panel (Windows 7). Other versions of Windows may have a different screen than what is shown in Figure 4. What is important is to locate the device manager.
- 6. Click on the Device Manager link.

🔊 🖓 👻 🕶 Control Panel 🕶 Al 🕯	Control Panel Items 🔻 System		✓ Go Search Control Panel
Control Panel Home	View basic information about	it your computer	
Device Manager	Windows edition		
Remote settings	Windows 7 Ultimate		
System protection	Copyright © 2009 Microsoft Corporation. All rights reserved.		
Advanced system settings	Service Pack 1		
,			E.
	System		
	Rating:	5.9 Windows Experience Index	
	Processor:	Intel(R) Core(TM)2 Duo CPU T9300 @ 2.50GHz 2.50 GHz	
	Installed memory (RAM):	8.00 GB	
	System type:	64-bit Operating System	
	Pen and Touch:	No Pen or Touch Input is available for this Display	
	Computer name, domain, and v	workgroup settings	
	Computer name:	mitekcorp	😌 Change settings
	Full computer name:	mitekcorp	
	Computer description:		
	Workgroup:	WORKGROUP	
	Windows activation		
	Windows is activated		atkits . I
	Product ID: 00426-065-27	21475-86497 Change product key	genuine Microsoft
			Learn more only
See also			
Action Center			
Windows Update			
Performance Information and Tools			



## DSP2210 / DSP2212

Quick Procedure for Updating the USB Driver

7. Click the "+" sign to expand the "Ports (COM & LPT)" section.



Figure 5

8. Mouse over the "USB Serial Port (COMX)" and right click.



RevA 3/15

specs are subject to change without notice. ATS005127

AII





Quick Procedure for Updating the USB Driver

9. Select "Search Automatically" and the PC will install the necessary update.



Figure 7

10. The PC may need to be restarted to complete the installation.

