



AA-ML

Optional Mic/Line Input Module for Atlas Sound
AA Series Model AA120M Mixer Amplifier



Applications

The AA-ML is an accessory input module for the AA120M. When inserted into the AA120M it can be used as an additional Line or Mic input. Unit features a level control, RCA style summing jacks for unbalanced line level signals, Phoenix style input for mic level signals with switchable 18V phantom power supply, remote VCA level control and 6 dB/octave high pass filter (-3 dB @ 300 Hz). Note: HPF is only functional for Mic input.

Technical Specifications

Microphone Input:	600 Ω Balanced
Sensitivity:	3mV
Line Input:	10K Ω Unbalanced
Sensitivity:	300mV
Microphone/Line Switch:	(PCB Jumper)
Mic Input Phantom Power:	+18V (PCB Jumper)
Mic Low-Cut Filter:	-10 dB at 100 Hz (PCB Jumper)
Output Level Control:	Front Panel Screwdriver Adjust
Remote Volume Control:	10K Pot
Terminations:	Mic Input = Phoenix terminals Remote Volume = Phoenix terminals Line/AUX = Dual RCA Summing Jacks

