



ACRL-191B/ACRL-291 Power Panels



ACRL-291

ACRL-291 Power Panels

The **ACRL-291** includes eight switched rear panel outlets plus one front panel un-switched outlet. A pull-out light bar is included on both the front and rear panels of the unit to provide illumination to both the front and rear of the rack. A 15 amp re-settable circuit breaker is located on the front panel for easy access. A 6' power cord is factory installed however a removable access panel and instructions are provided in the event the unit is to be hard-wired with conduit for permanent installations. UL Listing Pending.

Features

- Circuit Breaker Protected
- Heavy Duty AC Cord
- Rugged Steel Chassis
- **ACRL-291** Includes Front and Rear Pull Out Lights For Illumination Of Rack Mounted Equipment



ACRL-291 Front
Panel Light Extended



ACRL-291 Front
Panel Light Extended





ACRL-191B

ACRL-191B Power Panels

The **ACRL-191B** is equipped with a lighted, front-mounted rocker switch. It includes a re-settable 15-amp circuit breaker on the front panel with six switched and two un-switched outlets located on the back chassis and one un-switched outlet on the front panel.

ACRL-191B has a 6' factory installed power cord. A removable rear access panel is provided to allow the unit be hard-wired for permanent installation. Front panel is 16-ga. CRS and formed on two sides for recessed mounting. Finish is black epoxy.

Features

- Circuit Breaker Protected
- Heavy Duty AC Cord
- Rugged Steel Chassis

SPECIFICATIONS

MODEL	ACRL-191A	ACRL-191B	ACRL-291
PULLOUT LIGHTS	None	None	1Frt/1Rear
PANEL & SWITCH RATING	15 amps ea	15 amps ea	15 amps ea
OUTLETS SWITCHED	6	6	8
OUTLETS UNSWITCHED	2	3	1
DIMENSIONS	19"W x 1¾"H (1RU)	19"W x 1¾"H (1RU)	19"W x 1¾"H (1RU)



1601 Jack McKay Blvd.
Ennis, TX 75119
AtlasSound.com
Tech Support 1.800.876.3333

Printed in the USA
Specifications are subject to change without notice.

©Atlas Sound LP. Atlas Sound is a trademark of Atlas Sound LP. All rights reserved.

484206

000302

ATS001162 RevA 3/02